

# KYEC Safety Power Rails

Application of Crane · Hoist · Warehouse · Kinds of Assemble Line

Appointed  
Mark  
**KYEC**

ISO 9001  
Certificated  
Since Year  
2000



<b>Index</b>	Introduction	P1	3P-6P installment diagram	
	Choose suitable type and amperes	P2	1 type safety power rail design	P14
	3P-6P safety power rail design	P3	1 type safety power rail parts diagram	P15
	3P-6P parts diagram	P4	1 type safety power rail installment diagram	P17
	High temperature durable box safety power rail	P10	Our performance sample	end cover



## Introduction :

Being specialized in hoist repair and related innovation, KYEC provide our customers with excellent service based persistent devotion, responsibility and advanced technology.

In order to overcome the difficulties that we have been confronted with part importing, we dedicate ourselves to the production and innovation of parts and components. Also we have obtained numerous patents approved by R.O.C (Taiwan) and overseas countries.

KYEC supply our customers with readily available engineering materials and technical assistance to shorten time of preparation.

## Safety power rails

The safety power rails are electrical conductors of various profiles that are used to provide electrical potential to moving systems along a path of travel which have 3-6 poles.

The safety power rails are available for a current load from 60A up to 200A mobile electrification technology for moving transportation vehicles and equipment. Common application include: manufacturing robots, material handling systems, hoist and cranes, automated storage facilities and retrieval systems.

Safety power rail systems are available in a variety of configuration depending on applications requirements. Enclosed conductor systems typically enclosed conductors in a protective conduit meeting safety standard.



## General technical information

### Conversion Table of Horse Power

Full Load Current Table of 3 Phase Alternating

H.P.	100V	220V	440V	500V	2300V
10	4	2	1	0.8	
34	5.8	2.8	1.4	1.1	
1	7	3.5	1.8	1.4	
11.5/2	10	5	2.5	2.0	
2	13	6.5	3.3	2.8	
3		6	4.5	4	
5		10	7.5	6	
7.1/2		22	11	9	
12		27	14	11	
18		40	20	16	
25		52	26	21	
35		64	32	26	7
50		79	39	31	18.5
40		104	52	41	10.5
60		129	63	50	13
80		150	75	60	16
70		185	89	74	19
100		246	120	98	25
125		310	165	134	31
150		360	180	144	37
200		480	240	192	48

Check the steps below first to select the correct current (Ampere) of safety power rails and current collector:

1.Calculate the total motor Horse Power(H.P) required (ex.10H.P)

2.Multiply with the rated voltage(A.C.) (ex.230V)

3.Get the current data by checking the above conversion table (ex.27 Ampere)

### Safety Current Table of Conductor Wire Assembling

The safety current of safety power rails would perhaps be affected if the circuit temperature is over 35°C

Category of Conductor Wire	Dimension mm <sup>2</sup>	No. of Wires/Cables mm	Ampere Capacity(A)			
			60°C Insulator	70°C Insulator	80°C Insulator	90°C Insulator
Single Wire			1.6	25		
			2.0	36		
			2.5	46		
Shield Wire	2.0	70/8	25			
	3.5	70/8	25			
	5.5	71.0	45			
	6	71.2	55			
	14	71.8	80	70	60	50
	22	72.0	100	125	135	145
	30	72.3	125	150	160	170
	38	70.4	145	170	180	190
	50	79.1.6	175	210	220	230
	65	79.2.0	200	240	250	260
	80	79.2.5	230	285	305	330
	100	79.2.6	270	330	350	38
	125	79.2.8	310	380	400	440
	150	79.2.9	360	440	460	505
	200	81.2.6	425	530	550	600
	250	81.2.8	500	615	640	710
	300	81.2.8	590	720	780	830
	400	81.2.9	680	825	870	965
	500	81.2.2	750	930	985	1085

Horse power = total kws/0.75; A = Horse Power×3; (on the assumption 220V)

Total current [A.] ×1.25=proper current

According to the ampere quantity, choose the type of safety power rail:

90A - 200A: 3-GP safety power rail


150A: I type safety power rail

120A 320A 500A 800A: W type safety power rail


# 3P&4P&5P

## Vertical design

- 3P for 3 phase on R,S,T
- 4P for 3 phase on R,S,T and one ground wire
- 5P for 3 phase on R,S,T and two control line
- 6P for 3 phase on R,S,T and three line for saddle motor




## ① Vertical




Design as 3P & 4P Size


## ② Lateral



## ③ Above




## 3P Safety power rail



OFC 3N(99.9%, good conductivity)



3P (Phase) Safety Power Rail				
Type	Capacity (A)	Thickness (mm)	Width (mm)	Weight (kg/m)
KY-AN3007	75	2	10	0.8
KY-AN3010	100	2.8	10	1.03
KY-AN3015	150	3	10	1.24




Use with C Track Support  
and C Plate M10 Nut:  
30x20x5'



**KY-AN3100**  
3P Hanger Clamp  
0.075 kg / pc




**KY-AN3200**  
3P End Tension &  
Power In  
Fasten Block  
1.73 kg / pc



Type	Size	A	B
3P	70	62	
4P	90	62	
6P	130	122	

**KY-AN3300**  
3P Middle Power  
Feed-in  
0.21 kg / pc



Only M8x12L hex socket screw  
is for mounting this safety  
power rail.


1. Insert safety power rail into the hole
2. Use M8x12L hex socket screw to fix  
and tenser the safety power rail.  
(only two and half cycle needed when  
screws meet the safety power rail).
3. Power lines fixed with terminals,  
and fasten the copper power plate.

Power rail PVC, ped front.

**KY-AN3200**  
3P End Tension &  
Power In  
1.5 kg / pc


Only two and half cycle needed when  
screws meet safety power rail.

## 4P Safety power rail



DFC SN (99.9% good conductivity)

4P (Phase) Safety Power Rail				
Type	Capacity (A)	Thickness (mm)	Width (mm)	Weight (Kg/m)
KY-AN4007	75	2	10	1.1
KY-AN4010	100	2.8	10	1.6




Use with C Track Support  
and C Plate M10 Nut  
35x20x8




**KY-AN4100**  
4P Hanger Clamp

0.083 kg / pc



**KY-AN4200**  
End Tension &  
Power In

1.74 kg / pc



**KY-AN3703**


**KY-AN3705**

**KY-AN3703**  
30A Current  
Collector

0.24 kg / pc

**KY-AN3706**  
60A Current  
Collector

0.27 kg / pc




Riser rail PVC part free!

**KY-AN4200N**  
End Tension &  
Power In

1.28 kg / pc


## 5P Safety power rail



OFC (99.9% pure conductivity)  
Conductor Cross Section: 2.81X 10<sup>-26</sup>mm<sup>2</sup>

TYPE	CAPACITY (A)	THICKNESS (mm)	WIDTH (mm)	WEIGHT (kg/m)
KY-AN5039	100	2.8	10	1.7


SP power rails use the same middle tension as 6P.



Use with C Track Support  
and C Plate M10 Nut  
90x90x5 mm


**KY-ANS100**  
Hanger Clamp

0.09 kg / pc




**KY-AN5200**  
SP Middle Tension  
& Power In

1.75 kg / pc




Made to Order  
Twin Current  
Collector




**KY-AN3800**  
Fix Square Bar  
0.7 kg / pc

## 6P Safety power rail




OPC DIN (99.9%, good conductivity)


Type	Capacity (A)	Thickness (mm)	Width (mm)	Weight (kg/pm)
KY-AN6007	75	2	10	1.64
KY-AN6010	100	2.8	10	2.06




**KY-AN6100**  
6P Hanger Clamp  
0.1 kg / pc



**KY-AN6200**  
6P End Tension & Power In  
1.9 kg / pc




Power rail PVC pad fixed  
**KY-AN6200N**  
6P End Tension & Power In  
1.9 kg / pc




**KY-AN6300**  
6P Middle Tension & Power In  
0.38 kg / pc

3P 200A Parts Diagram



CFC-3M (99.9%, good conductivity)


3P(Phase) Safety Power Rail		
Type	Standard	kg/m
KY-AN3020	200 Amp	1.42



Use with C Track Support  
and C Plate Mitre Kit



**KY-AN3120**  
3P Hanger Clamp  
0.075 kg / pc



**KY-AN3220**  
3P End Tension &  
Power in:  
1.75 kg / p

---

KYEC Safety Power Ball Test Result


Galvanic Corrosion Test Results						
Tort Type	Material	Resistance coefficient (R m)	Dissolve Potential	Decay of Potential (mV/h)	200mA/10hrs Decay Percentage	Temperature
W-type 300A	Aluminum	0.000190	8KV x 30min	0.06	3.6%	23
W-type 500A	Aluminum	0.000157	8KV x 30min	0.054	3.5%	23
W-type 220A	Aluminum & Copper	0.000184	8KV x 30min	0.059	3.7%	23
3P 100A	Copper	0.000630	8KV x 30min	0.057	2.9%	23
3P 100M	Copper & Stainless Steel	0.000812	8KV x 30min	0.047	2.1%	23
3P-TSA	Copper	0.000582	8KV x 30min	0.066	3.0%	23

Ansys Institute | Industrial Technology Research Institute

**Assay Instrument:** Brand & Model : ESI 242B  
KIKUSUI TOS-8700  
TAMA-TDV-20AADS  
**Name of instrument :** PRECISION RESMEASUREMENT SYSTEM  
WITHHOLDING VOLTAGE TESTER  
HIGH VOLTAGE DIGITAL METER


#### 3P 100A (Copper)

Length (cm)	90	95	100	40	50	60	70	80	90	100
Percent of Maximum	0.87	1.04	1.71	0.78	0.86	1.01	1.29	1.56	1.12	1.39




#### 3P 100A (Stainless Steel)

Length (M)	12	26	38	40	50	68	73	80	96	120
Number of Participants	347	326	141	186	238	232	320	376	423	433




## 4P 200A Parts Diagram




GFG 3N (99.9%, good conductivity)  
Conductor Cross Section: 3.84<sup>2</sup> mm<sup>2</sup> / 1.6mm<sup>2</sup>

4P(Phase) Safety Power Rail		
Type	Standard	kg/m
KY-AN4020	200 Amp	1.9




Use with G Track Support  
and G Plate M10 Nut  
30 X 20 mm


KY-AN4120
4P Hanger Clamp
0.083 kg / pc



KY-AN4220
4P End Tension & Power In
1.75 kg / pc



KY-AN3710
N Current Collector 100A
0.36 kg / pc




KY-AN4300
4P Middle Tension & Power In
0.34 kg / pc



[Illustration of a coupling with a current collector and power supply.]
With Coupling with current collector with power supply, it can clean power rails in movement.

Clean Brush Produciton on Demand
--



## High Temperature Durable Box Safety Power Rail



**KY-D3003 (6133)**  
ND3P Straight Line Duct  
3 kg / M



**KY-D3702 (6175)**  
ND3P Trolley 20A  
0.7 kg / pc




**KY-D3500 (61331)**  
ND3P Coupling Plate  
0.3 kg / pc




**KY-D3704 (6276)**  
ND3P Trolley 40A  
0.8 kg / pc



**KY-D3100 (6111)**  
ND3P Hanger  
0.3 kg / pc




**KY-D3600 (6117)**  
ND3P Trolley Pulling Bracket



**KY-D3201 (6112)**  
ND3P End Cap  
0.4 kg / pc



**KY-D3001 (6001)**  
ND3P Trolley Collectors  
**KY-D3902 (6102)**  
ND3P Trolley Collectors 20A  
**KY-D3904 (6104)**  
ND3P Trolley Collectors 40A



**KY-D3200 (6173)**  
ND3P Feed-in Boxes  
1.2 kg / pc




**Produce on Demand**  
Curved Duct



## 3P ~ 6P Installments Diagram

### Step 1 Support Design



#### Remark :

- (1) The side design installment recommended when a cantilever posture to the 3-6P safety power assembly.
- (2) The hanger clamp are supposed to be installed every 0.5 meter from the starting point of the living.
- (3) The 2-6P tension part for safety power rails must be installed at the place about 10mm higher than the hanger clamp.

This step prevents water from flowing to the power-in place along the safety power rail, hence the short circuit won't happen.


(4) The silica gel must be coated on the connected place of the power-in part and safety power rail as weather protection.

(5) The 3-6P safety power rails are not suitable for outdoor usage or the place with high acid/salt environments.



### Step 2 End tension & Power-in

Remark : (1) Install one end on the ground then lift up to estimated location and install another.

### Step 3 Hanger clamp





### Step 4 End tension & Power-in





- To avoid short circuit, please fasten the terminal plate with M8 x 16mm socket screws.

## Step 5 Fix square bar/current collector



### Remark:

- 1) Fix square bar could be welded on the frame or screwded.
- 2) Fix square bar's angle is supposed to be mounted. One diagonal of the bar must be parallel to ground and safety power rail, another is vertical.
- 3) Length could be cut as demands.
- 4) If carbon brushes wear, just replace a new one.



## QUESTIONNAIRE


Please fill out the form. For curve tracks, we require drafts to prepare a quotation.

Company: \_\_\_\_\_ Tel: \_\_\_\_\_ Fax: \_\_\_\_\_



E-Mail: \_\_\_\_\_

1. Number of power rail installations: \_\_\_\_\_
2. Type of equipment to be powered: \_\_\_\_\_
3. Voltage: \_\_\_\_\_ V, Phases: \_\_\_\_\_, Frequency: \_\_\_\_\_ Hz  AC  DC
4. Track length: \_\_\_\_\_ m; travel speed: \_\_\_\_\_ m/min.  Indoor  Outdoor plant
5. Number of power rails: \_\_\_\_\_ (main rails: \_\_\_\_\_ control rails: \_\_\_\_\_ ground rail: \_\_\_\_\_)
6. Type of power rail:  Combine(3P-6P power rail)  Power rail respectively(I type)
7. Other operating conditions (humidity, dust, chemical influence etc.) \_\_\_\_\_
8. Ambient temperature: \_\_\_\_\_ °C min. \_\_\_\_\_ °C max.
9. How are the rails laid out? (Please provide draft): \_\_\_\_\_
10. Power consumption of the individual consumer loads: \_\_\_\_\_ (consult page 2)
11. Max. voltage drop from the power rail feed to the consumer unit: \_\_\_\_\_
12. Remarks: \_\_\_\_\_

### 3P Rail connector and middle power In




- (1) Cut off the PVC material at 25mm from the end of safety power rail.
- (2) Bend upward copper material in vertical 90°angle.
- (3) Insert both sides of 90°vertical angle safety power rail into middle power feeding and connect both sides by screwing up M6 inner hexagon screw bolt on U-type copper connector.



Mini Current Collector		
Type	Standard	kg/pce
KY-AN37033	30 Amp	0.14
KY-AN37066	60 Amp	0.17
KY-AN37101	100 Amp	0.27

Double set is available as photo, type for example is KY-AN37033D.


### Current Collector Unit




### Transit & Test System



#### Moving Power Supply Location




## ● I type safety power rail installment diagram




• On Side Installation



• Vertical Installation Double



• Above Installation




A	minimum	75
	standard	100

B	B 1	95
	B 2	130
	B 3	280

C	minimum	150
	standard	200

## 1 type safety power rail Parts Diagram




OFC 99.9% (99.9%, good conductivity)

**KY-AN1015**

"I" Type Rail

0.47 kg / M




Use with C Rail Support  
and C Plate M10 Nut  
32 x 26 x 5"

**KY-AN1100**

"I" Type  
Hanger Clamp


0.11 kg / pc



**KY-AN1200**


"I" Type End  
Tension & Power in

1.1 kg / pc



+100Amp

+40Amp



Carbon brush


0.83 kg / pc

1.17 kg / pc

**KY-AN1704**

**KY-AN1710**

40/100 Amp  
Current Collector




**KY-AN1838 380L**

**KY-AN1850 500L**

Insulator Guide

1.45 kg / pc


1.82 kg / pc



KY-AN1300

"I" Type Middle power feed in


0.26 kg / pc



KY-AN1600

Fixed end insulator


0.07 kg / pc



KY-AN1100S


"I" Type Insulator hanger

0.15 kg / pc




Produce on Demand

Intermediate tension insulator



+100Amp



Carbon brush

+40Amp



KY-AXE0804

KY-AXE0810

40/100 Amp Current Collector


A = Aluminum body

For "8" type power rail


## 1 type safety power rail Installment diagram

## Step 1 Support Design


#### A. installment for 1 type in 30 meters




#### B. installment for I type over 30 meters




### **Line Case**




### Curve Cast



### • Around type




#### “S” type




#### ● Around & Relief type

1. Distance of each hanger clump must be under 0.5m in around type.
  2. The way to pull up rail is use traverse table put on the saddle's beam, pull up the rail when crane moves. (As the commentary picture no.3 shown in end cover)


## Step 2 Length in 30M




Length over 30M



### **Step 3 Set & Hanger Clamp**





- Use tool to clip inward Plastic Clip and pull I-Type Insulated Conductor Holes out together if necessary.



- (1) Cut off 10mm long of insulated material PVC in the middle of I-Type Insulated Conductor Rats for supplying power.
- (2) Contact Copper Conductor of I-Type Insulated Conductor Rats by two piece of Copper Plate and fix it by M4 linear hexagon screw bolt.
- (3) Drill two holes ø 6mm through both Copper Plate and Copper conductor of I-Type Insulated Conductor Rats at the bottom and insulation, so conductive need the holes.


#### **Step 4 Set, End Tension & Power in**

#### **Step 5 Set, guide & Current Collector**



(1) If a square bar's angle is supposed to be measured, one diagonal of the bar must be parallel to ground and safety power rail, another is vertical.  
(2) Length could be cut as damaged.

© Cowtlen



- (1) It is not allowed to incline over 15° when install I-Type Insulated Conductor Rails.
  - (2) If I-Type Insulated Conductor Rails fall incline after installation, then it is required to adjust formerly.



### Commentary

① Current Collector Set  
② For Hoist

③ Around Set  
④ For Hoist (Curve Track)

⑤ Amusement Grounds  
⑥ Warehouse



**KYEC**

Kunyee Industrial ltd.  
<http://www.kyec-mit.com.tw>  
email : taiwan.kyec@msa.hinet.net

Head Office	TEL.:+86-5-3287888	FAX:+86-5-3286778
Taipei Branch	TEL.:+86-2-2394-8345	FAX:+86-2-2396-8848
TaiChung Branch	TEL.:+86-4-2358-0075	FAX:+86-4-2358-2646
Kaohsiung Branch	TEL.:+86-7-384-9997	FAX:+86-7-383-8729